



FEATURES

- Wireless transmitter for the AMPLICALL range
- Need to be paired with an AMPLICALL 100 or/and an AMPLICALL 150
- Emergency call button (when paired with AC100 or AC150)
- Adjustable sound detection time (1/5/15s)
- Adjustable detection sensitivity: High (75dB) / Medium (84dB) / Low (90dB)
- Range between the emitter and the receiver:
 - Indoor: up to 35m
 - Open field: up to 200m

TECHNICAL SPECIFICATIONS

- Wall and desk mountable
- Works with a 5V DC USB type C adaptor (included) and with 2 AA batteries (not included)
- Sound detector (internal microphone or external piezo)
- External piezo with 3,5mm jack cable (30cm) + extension jack cable (1m50) for external microphone
- Frequency: 868Mhz
- Dimensions: 10,1 x 9,8 x 3,6 cm

WORKS WITH:

- AMPLICALL 100, AMPLICALL 150

